

# MP260U 60W 6 Zones USB/SD/FM Mixer Amplifier



## Features

- Built-in MP3/Tuner/USB/SD card inputs
- 6 zones output with pre-amplifier, 6 channels @ 100V outputs
- 3 LINE& 2 MIC inputs with individual volume control
- Mute function, easy to insert priority broadcast
- Each zone with independent switch; bass and treble controlled
- With level indicators and 5-unit LED display
- Output short-circuit protection

## Description

MP260U is a 60W 6 channel USB/SD/FM Mixer Amplifier for public address. It integrates 3 audio sources-USB, SD and FM and 6 channels. It has 2 microphone inputs and 3 extra aux inputs, and Mic 1 is provided with priority and muting function. Bass and treble controls and master volume control are provided. Complete protection includes short circuit and thermal protection, current limiter and overloading.

This amplifier can be applied to different cases, such as supermarket, classroom, bank, church, school, hotel, restaurant, theme centers and shopping center, etc.

## ***SPECIFICATION***

Model	MP260U
Rated output	60W
Output regulation	Less than 3dB
Speaker output	100V
AUX output	1V
Input Sensitivity	Mic1,2 : 3mV( $\pm$ 0.5mV) unbalanced
	Line 1,2,3 : 300mV( $\pm$ 30mV) unbalanced
Frequency response	65Hz-20kHz ( $\pm$ 3dB)
Distortion	Less than 1% at 1kHz , 1/3 rated output voltage
The ratio of signal to noise ratio	Mic1 and 2 : Bigger than 80dB
	Line 1、 2 and 3 Bigger than 80dB
Tone	Bass : $\pm$ 12dB at 100Hz
	Treble : $\pm$ 12dB at 10kHz
FM	87.5MHz-108.0MHz
MP3 Input Sensitivity	230-280mV
Protection	AC fuse; DC voltage; overload; short-circuit.
Muting function	Mic1 overrides other input signals with 0 ~ -30dB attenuation
Power requirements	AC 220-240V/50-60Hz
Power consumption	100W
Dimensions	485×340×88mm
Gross weight	8.5kg
Net weight	7.2kg

Specifications are subject to change without notice